

SECTION VI : APPENDICES

1. Parts List for MS-2931

A Mark: Antistatic Parts
 M Mark: Moisture Protection parts
 S Mark: Safety related parts
 X Mark: X-ray radiation related parts
 OR: Substitute for the parts above

Contents

1	ASS'Y CHASSIS UNIT	Page 2
	ASS'Y PCB MAIN	Page 2
	ASS'Y PCB CRT	Page 12
	OTHERS	Page 13
2	OTHERS	Page 14
3	ASSEMBLED PARTS	Page 14

2. Electric Diagram

- * CONNECTION DIAGRAM
- * SCHEMATIC DIAGRAM for PCB-MAIN
- * SCHEMATIC DIAGRAM for PCB-CRT

A M S X	SYMB.	CODE	NAME	DESCRIPTION	QTY
1. ASS'Y CHASSIS UNIT					
***** ASS'Y PCB MAIN *****					
S	BD901	00N25197A4	D-BRIDGE	RBV-606	1
	C101	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
	C102	0KP04102KB	CP-C-CERAMIC	GRM39 50V B 102K PT	1
	C103	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
	C104	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
	C105	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C106	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
	C107	0KP03471JC	CP-C-CERAMIC	GRM39 50V CH 471J PT	1
	C108	0KP03471JC	CP-C-CERAMIC	GRM39 50V CH 471J PT	1
	C109	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C110	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C111	0KK86332JM	CP-C-CERAMIC	GRM40 50V SL 332J PT	1
	C112	0KP04472KB	CP-C-CERAMIC	GRM39 50V B 472K PT	1
	C201	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
	C202	0EP88470MW	C-EL	KMA 16V 47MF-M TP 6.3X7	1
	C203	0EP88101MW	C-EL	KMA 16V 100MF-M TP 7X7	1
	C221	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C222	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C223	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C224	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C225	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C226	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C227	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C228	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C229	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C230	0KT912R2MT	C-EL	YXA 50V 2.2MF-M TP 5X11	1
	C231	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
	C232	0ET91101MT	C-EL	YXA 16V 100MF-M TP 5X11	1
	C233	0KT91220MT	C-EL	YXA 50V 22MF-M TP 5X11	1
	C234	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
	C351	0KP03300JC	CP-C-CERAMIC	GRM39 50V CH 300J PT	1
	C352	0KP03300JC	CP-C-CERAMIC	GRM39 50V CH 300J PT	1
	C353	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
	C354	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C355	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C356	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
	C357	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C360	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C361	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
	C362	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
	C363	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C381	0GT91101MT	C-EL	YXA 25V 100MF-M TP 6.3X11	1
	C401	0GT50101MT	C-EL	PJ 25V 100MF-M TP 6.3X15	1
	C402	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C404	0NT40274JT	C-PLASTIC	ECQ-V1 274J M3 (TP)	1
	C406	0KT50101MT	C-EL	PJ 50V 100MF-M TP 8X20	1
	C407	0GT50101MT	C-EL	PJ 25V 100MF-M TP 6.3X15	1
	C451	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C452	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
	C453	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
	C454	0NM871R0MW	C-EL	KME 100V 1MF-M TP 5X11	1
	C455	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
	C501	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
	C502	0RP87103JF	C-PLASTIC	ECQ-E 2103J F3	1
	C503	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
	C505	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
	C506	0GT91331MT	C-EL	YXA 25V 330MF-M TP 10X12.5	1
	C511	02K1E822HF	C-PLASTIC	ECWH20822HVB	1
	C512	02K1E752HF	C-PLASTIC	ECWH20752HVB	1
	C513	06K1E153HF	C-PLASTIC	ECWH16153HVB	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				C514	06K1E153HF	C-PLASTIC	ECWH16153HVB	1
				C516	0RT32364JF	C-PLASTIC	ECWF2364JBB	1
				C517	0RT32394JF	C-PLASTIC	ECWF2394JBB	1
				C518	0RT32334JF	C-PLASTIC	ECWF2334JBB	1
				C519	0RT32105JF	C-PLASTIC	ECWF2105JBB	1
				C520	0RT32914JF	C-PLASTIC	ECWF2914JBB	1
				C531	0IT50331MT	C-EL	PJ 35V 330MF-M TP 10X20	1
				C532	0IT50331MT	C-EL	PJ 35V 330MF-M TP 10X20	1
				C533	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C534	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C535	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
				C601	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
				C602	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C603	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C604	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C605	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C606	0KQ16334J1	C-PLASTIC	ECQ-V1H 334J L3 (TP)	1
				C607	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
				C608	0KT91330MT	C-EL	YXA 50V 33MF-M TP 5X11	1
				C609	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C610	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C611	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C612	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C613	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C614	0ET91471MT	C-EL	YXA 16V 470MF-M TP 8X11.5	1
				C615	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C616	0FP08104M1	CP-C-TANTAL	TEMSVA21D104M-8R	1
				C617	0KQ16104J1	C-PLASTIC	ECQ-V1H 104J L3 (TP)	1
				C618	0KP03471JC	CP-C-CERAMIC	GRM39 50V CH 471J PT	1
				C619	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C620	0KP04222KB	CP-C-CERAMIC	GRM39 50V B 222K PT	1
				C621	0KT912R2MT	C-EL	YXA 50V 2.2MF-M TP 5X11	1
				C622	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C623	0KP03101JC	CP-C-CERAMIC	GRM39 50V CH 101J PT	1
				C624	0KT911R0MT	C-EL	YXA 50V 1MF-M TP 5X11	1
				C625	0KP764R7MT	C-EL	KME-BP 50V VB 4.7MF-M TP 5X11	1
				C626	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C627	0KP04102KB	CP-C-CERAMIC	GRM39 50V B 102K PT	1
				C628	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C629	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C630	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C631	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C632	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C633	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C634	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C702	0RQ646R8MP	C-EL	KXB 250V 6.80MF-M MC 18X40	1
				C703	0ZK1F224JF	C-PLASTIC	ECQ-E 10224J FB	1
				C704	06H73102JF	C-PLASTIC	DKR 1600V 102J SRT	1
				C705	0NK50682JM	C-PLASTIC	DTW 100V 682J TP	1
				C711	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C712	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C713	0KH81472KB	C-CERAMIC	DD107-959 B 472K 50V TP	1
				C721	0ET91101MT	C-EL	YXA 16V 100MF-M TP 5X11	1
				C722	0KP764R7MT	C-EL	KME-BP 50V VB 4.7MF-M TP 5X11	1
				C723	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C724	0RP97224KF	C-PLASTIC	ECQ-E 2224K F3	1
				C731	0RP97104KF	C-PLASTIC	ECQ-E 2104K F3	1
S				C901	0RP15104MS	C-PLASTIC	LFX 250V 104M	1
S				C902	0RT04102ME	C-CERAMIC	DE0910-778 E 102M-KX	1
S				C903	0RT04102ME	C-CERAMIC	DE0910-778 E 102M-KX	1
S				C904	0RT04222ME	C-CERAMIC	DE1210-778 E 222M-KX	1
S				C905	0CJ1D122M1	C-EL	MXC 200V 1200MF-M 30X40	1
S				C905	0QT35122M1	C-EL	GU 200V 1200MF-M 30X40	CR
				C906	0UP56104JF	C-PLASTIC	ECQ-E 4104J FB	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				C907	0ZQ49102KR	C-CERAMIC	DE0905-979 R 102K 1K	1
				C908	0ZQ49102KR	C-CERAMIC	DE0905-979 R 102K 1K	1
				C909	02P43102KR	C-CERAMIC	DE1210-1 (H)R 102K 2KV SRT	1
				C910	0IT91471MT	C-EL	YXA 35V 470MF-M TP 10X16	1
				C911	0GP04223KE	CP-C-CERAMIC	GRM39 25V B 223K PT	1
				C912	0GP03561JC	CP-C-CERAMIC	GRM39 25V CH 561J PT	1
				C913	0EK90474KB	CP-C-CERAMIC	GRM40 16V B 474K PT	1
				C914	0KP04103ZF	CP-C-CERAMIC	GRM39 50V F 103Z PT	1
				C915	0EK90334KB	CP-C-CERAMIC	GRM40 16V B 334K PT	1
				C916	0KK90223KB	CP-C-CERAMIC	GRM40 50V B 223K PT	1
				C921	0RT28471M2	C-EL	MXC 250V 470MF-M 22X45	1
				C921	0RT85471M1	C-EL	GU 250V 470MF-M 22X50	OR
				C922	0GT50222MP	C-EL	PJ 25V 2200MF-M 12.5X40	1
				C923	0CT50222MP	C-EL	PJ 10V 2200MF-M MC 12.5X25	1
				C924	0GT50681MP	C-EL	PJ 25V 680MF-M 10X31.5	1
				C925	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C926	0RP87473JF	C-PLASTIC	ECQ-E 2473J F3	1
				C927	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C928	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
				C929	0ET91221MT	C-EL	YXA 16V 220MF-M TP 6.3X11	1
				C930	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C931	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C951	0GP04104ZF	CP-C-CERAMIC	GRM39 25V F 104Z PT	1
				C952	0RP87104KF	C-PLASTIC	ECQ-E 2104K F3	1
				C953	0RJ1E470MP	C-EL	KMX 250V 47MF-M MC 16X25	1
				C954	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
				C955	0GP03102JC	CP-C-CERAMIC	GRM39 25V CH 102J PT	1
				C956	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
				C957	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C958	0RP87103JF	C-PLASTIC	ECQ-E 2103J F3	1
				C959	0KK90223KB	CP-C-CERAMIC	GRM40 50V B 223K PT	1
				C960	0KT91100MT	C-EL	YXA 50V 10MF-M TP 5X11	1
				C961	0ET91470MT	C-EL	YXA 16V 47MF-M TP 5X11	1
				C962	0KP03820JC	CP-C-CERAMIC	GRM39 50V CH 820J PT	1
				C963	0KP04103KB	CP-C-CERAMIC	GRM39 50V B 103K PT	1
				C971	0EP76100MT	C-EL	KME-BP 16V VB 10MF-M TP 5X11	1
				C972	0EK90105ZF	CP-C-CERAMIC	GRM40 16V F 105Z PT	1
				C973	0KP04102KB	CP-C-CERAMIC	GRM39 50V B 102K PT	1
				CN102	05V03381A1	ASSY HARNESS	ASSY HARNESS CN102	1
				CN201	00J40273A5	CN	B6B-EH (RED)	1
				CN202	00J40190A5	CN	B6B-EH	1
				CN251	08R40362A1	CN-D-SUB	CHS3115-0126	1
				CN251	30M0D007A1	CN-D-SUB	5510-15S-RC-Z	OR
				CN252	05V03383A1	ASSY HARNESS	ASSY HARNESS CN101	1
				CN351	00J40642A5	CN	B6B-PH-K-S	1
				CN352	00J40642A3	CN	B4B-PH-K-S	1
				CN353	00J40644A3	CN	S4B-PH-K-S	1
				CN401	00F40752A2	CN	W-P3002(2P)	1
				CN511	08F40149A2	CN	B2P-LV-TN	1
				CN703	05V03382A1	ASSY HARNESS	ASSY HARNESS CN703	1
	S			CN901	00F40916A1	CN	B2P3-VH	1
	S			CN903	00F40019A1	CN	YP115S-2P	1
				CN904	00J40642A1	CN	B2B-PH-K-S	1
				CN951	00J40190A1	CN	B2B-EH	1
A				D101	08H25035C1	CP-D	DAN217 (T146)	1
A				D102	00H25737C1	CP-D	DAN202K (T146)	1
A				D103	08H25657A1	CP-D	1SS355 (TE17) TP	1
A				D104	08H25035C1	CP-D	DAN217 (T146)	1
A				D105	08H25035C1	CP-D	DAN217 (T146)	1
A				D201	08H25035C1	CP-D	DAN217 (T146)	1
A				D202	08H25035C1	CP-D	DAN217 (T146)	1
A				D203	08H25035C1	CP-D	DAN217 (T146)	1
A				D204	08H25657A1	CP-D	1SS355 (TE17) TP	1
A				D221	08H25035C1	CP-D	DAN217 (T146)	1

A	MIS X	SYMB.	CODE	NAME	DESCRIPTION	Q'TY
A		D222	08H25035C1	CP-D	DAN217 (T146)	1
A		D223	08H25035C1	CP-D	DAN217 (T146)	1
A		D381	08H25035C1	CP-D	DAN217 (T146)	1
A		D382	08H25035C1	CP-D	DAN217 (T146)	1
A		D383	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D401	08F25847T1	D	ERA18-02V3 TP	1
A		D451	08H25035C1	CP-D	DAN217 (T146)	1
A		D452	08H25035C1	CP-D	DAN217 (T146)	1
A		D453	08H25737C1	CP-D	DAN202K (T146)	1
A		D501	08H25657A1	CP-D	1SS355 (TE17) TP	1
A		D503	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D511	08N25211A2	D	DD54RCLS	1
		D512	08F25847T1	D	ERA18-02V3 TP	1
A		D513	08H25657A1	CP-D	1SS355 (TE17) TP	1
A		D514	08H25657A1	CP-D	1SS355 (TE17) TP	1
A		D515	08H25657A1	CP-D	1SS355 (TE17) TP	1
A		D517	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D531	09H25134C1	CP-D	U1DL44A (TE12L)	1
		D532	09H25134C1	CP-D	U1DL44A (TE12L)	1
		D536	08H25119A1	CP-D	HSM83-TL	1
		D537	08H25119A1	CP-D	HSM83-TL	1
A		D601	08H25035C1	CP-D	DAN217 (T146)	1
		D602	08F25847T1	D	ERA18-02V3 TP	1
		D603	09H25134C1	CP-D	U1DL44A (TE12L)	1
		D701	08N25917T1	DIODE	1GU42A (TPA3)	1
		D702	08N25917T1	DIODE	1GU42A (TPA3)	1
		D703	08N25238T1	D	05NU42 (TPA3)	1
A		D704	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D705	08N25238T1	D	05NU42 (TPA3)	1
		D706	08N25917T1	DIODE	1GU42A (TPA3)	1
		D711	08N25030T1	D	1SS244 T-77	1
A		D721	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D731	09H25134C1	CP-D	U1DL44A (TE12L)	1
		D901	08N25030T1	D	1SS244 T-77	1
		D902	08G8F003F1	D	1R5JU41 (LC7-15)	1
		D902	08R25431F1	D	ERC38-06E	OR
		D903	08J25562T1	D	11EFS2-TA1 B2	1
A		D904	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D921	08N25321A1	D	5JLZ47	1
		(D921)	08NCD024A1	RADIATOR	BPUE10-35	1
		(D921)	08NCD024A1	RADIATOR	BPUE10-35	OR
		(D921)	08R49039A2	RADIATOR	OSH-1035-SPL	OR
		(D921)	08R49039A2	RADIATOR	OSH-1035-SPL	OR
		(D921)	08FF623010D	SCREW	SC-SEMS-P-PAN M3X10(W/SW) ZN/FE	1
		D922	08J25103F1	D	ERC84-009L	1
		D923	08J25103F1	D	ERC84-009L	1
		D924	08J25378A1	D	RL2Z LF-B2	1
		D925	08J25562T1	D	11EFS2-TA1 B2	1
A		D926	08H25737C1	CP-D	DAN202K (T146)	1
		D927	08J25562T1	D	11EFS2-TA1 B2	1
A		D928	08H25657A1	CP-D	1SS355 (TE17) TP	1
		D929	09H25134C1	CP-D	U1DL44A (TE12L)	1
A		D930	08H25035C1	CP-D	DAN217 (T146)	1
		D951	08N25030T1	D	1SS244 T-77	1
		D952	08R25170A2	D	1R5GU41	1
A		D953	08H25657A1	CP-D	1SS355 (TE17) TP	1
A		D954	08H25657A1	CP-D	1SS355 (TE17) TP	1
S		F701	08N32018A1	FUSE	215001 1A	1
S		F901	08N32018A9	FUSE	21506.3	1
		FC701	08N51217T1	FUSE-HOLDER	PFC5000-0202	1
		FC702	08N51217T1	FUSE-HOLDER	PFC5000-0202	1
		FC901	08N51217T1	FUSE-HOLDER	PFC5000-0202	1
		FC902	08N51217T1	FUSE-HOLDER	PFC5000-0202	1
		L201	08K00101K0	L-PEAKING	ELC606RA-101K TP	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				L512	05F16750A1	H.LIN	ETS75	1
				L513	00M22331K1	L-CHOKE	LHL10TB331K TP	1
				L514	00M22102J1	L-CHOKE	LHL10TB102J TP	1
				L531	00M22681K1	L-CHOKE	LHL10TB681K TP	1
				L533	00M22100K1	L-CHOKE	LHL10TB100K TP	1
				L534	00M22100K1	L-CHOKE	LHL10TB100K TP	1
				L601	00K00101K0	L-PEAKING	EL0606RA-101K TP	1
				L701	00M22101K1	L-CHOKE	LHL10TB101K TP	1
				L702	00M223R3M1	L-CHOKE	LHL10TB3R3M TP	1
				L703	09F50164T1	NF	BL02RN1-R62T2	1
				L721	00K00101K0	L-PEAKING	EL0606RA-101K TP	1
	S			L901	00F1H011A1	L-LINE-F	ELF20N027A	1
				L902	09F50164T1	NF	BL02RN1-R62T2	1
				L921	00M22101K1	L-CHOKE	LHL10TB101K TP	1
				L922	00K00101K0	L-PEAKING	EL0606RA-101K TP	1
				L923	00K00101K0	L-PEAKING	EL0606RA-101K TP	1
				L924	00M22101K1	L-CHOKE	LHL10TB101K TP	1
				L925	00M21101K1	L-CHOKE	LHL08TB101K TP	1
				L926	00M213R3M1	L-CHOKE	LHL08TB3R3M TP	1
				L951	05F16751C1	L-CHOKE	A3400969	1
				L952	00K00101K0	L-PEAKING	EL0606RA-101K TP	1
				L953	01F38923T9	CP-COIL	BLM11A221SPT TP(SMD)	1
				L954	01F38923T9	CP-COIL	BLM11A221SPT TP(SMD)	1
	S			NTH901	08N38366A1	R-THERMISTOR	NTH22D6R0LA	1
	S			PC901	09F28369A2	IC-PC	TLP721F D4-GRLM	1
	S			PTH901	08J29031B1	R-POSISTOR	PTH451C263BG8R0M140A	1
A				Q101	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q102	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
A				Q201	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q202	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q203	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q204	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
A				Q205	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
A				Q206	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
				Q207	0AK41364ZZ	CP-TR	2SA1364	1
A				Q208	00H29365T1	CP-TR-DIGITAL	DTC143EK T-146	1
A				Q221	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q222	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q351	00H29358T1	CP-TR-DIGITAL	DTC144EK T-146	1
A				Q381	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
A				Q501	0KG12961ZZ	TR-FET	2SK2961 TP	1
A				Q502	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
				Q503	0BF21569AE	TR	2SB1569A-E	1
				(Q503)	30N0D024A1	RADIATOR	BPUE10-35	1
				(Q503)	00N0D024A1	RADIATOR	BPUE10-35	OR
				(Q503)	38R49039A2	RADIATOR	OSH-1035-SPL	OR
				(Q503)	08R49039A2	RADIATOR	OSH-1035-SPL	OR
				(Q503)	0FF623010D	SCREW	SC-SEMS-P-PAN M3X10(W/SW) ZN/FE	1
A				Q504	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
A				Q505	0AK41037KZ	CP-TR	2SA1037K T-146 Q,R,S	1
				Q511	0CF25244NZ	TR	2SC5244-NU	1
	S			(Q511)	08R52554A1	INSULATOR	BFG45(25X30)D-7 DSN-CSSX-G53002(UL)	1
A				Q512	01H29733T2	CP-TR-DIGITAL	DTC143ZKA T-146	1
A				Q513	01H29733T2	CP-TR-DIGITAL	DTC143ZKA T-146	1
A				Q514	01H29733T2	CP-TR-DIGITAL	DTC143ZKA T-146	1
A				Q515	01H29733T2	CP-TR-DIGITAL	DTC143ZKA T-146	1
				Q531	0CH24002ZE	TR	2SC4002-E TP	1
A				Q601	00H29340T1	CP-TR-DIGITAL	DTA144EK T-146	1
A				Q701	09F24556A1	TR-FET	2SK2847	1
A	S			Q901	00G8A004A1	TR-FET	FS18RM-10 A8	1
				(Q901)	00N0D002A1	RADIATOR	OSV-15100C-L65-BPWL	1
				(Q901)	0FF623010D	SCREW	SC-SEMS-P-PAN M3X10(W/SW) ZN/FE	1
A				Q921	00H29365T1	CP-TR-DIGITAL	DTC143EK T-146	1
A				Q922	01H29733T2	CP-TR-DIGITAL	DTC143ZKA T-146	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
A				Q951	0AK41721ZZ	CP-TR	2SA1721-O(TE85L)	1
A				Q952	0JG00512ZZ	TR-FET	2SJ512	1
A				Q971	0CK42412KZ	CP-TR	2SC2412K T-146 Q,R,S	1
				R101	0ZL49302JA	CP-R-CARBON	RK73K2A 1/10W 3.0K-J TP(TD)	1
				R102	0ZL49334JA	CP-R-CARBON	RK73K2A 1/10W 330K-J TP(TD)	1
				R103	0ZL49334JA	CP-R-CARBON	RK73K2A 1/10W 330K-J TP(TD)	1
				R104	0ZL49393JA	CP-R-CARBON	RK73K2A 1/10W 39K-J TP(TD)	1
				R105	0ZL49334JA	CP-R-CARBON	RK73K2A 1/10W 330K-J TP(TD)	1
				R106	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R107	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R108	0ZL49393JA	CP-R-CARBON	RK73K2A 1/10W 39K-J TP(TD)	1
				R109	0ZL49681JA	CP-R-CARBON	RK73K2A 1/10W 680-J TP(TD)	1
				R110	0ZL49392JA	CP-R-CARBON	RK73K2A 1/10W 3.9K-J TP(TD)	1
				R111	0ZL49823JA	CP-R-CARBON	RK73K2A 1/10W 82K-J TP(TD)	1
				R112	0ZL49182JA	CP-R-CARBON	RK73K2A 1/10W 1.8K-J TP(TD)	1
				R113	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R114	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R115	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R116	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R117	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R118	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R119	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R120	0ZL49393JA	CP-R-CARBON	RK73K2A 1/10W 39K-J TP(TD)	1
				R201	0ZL481501F	CP-R-CARBON	RK73H2A 1/10W 1.50K-F TP(TD)	1
				R202	0BL4875R0F	CP-R-CARBON	RK73H2E 1/4W 75.0-F TP(TD)	1
				R203	0ZL49332JA	CP-R-CARBON	RK73K2A 1/10W 3.3K-J TP(TD)	1
				R204	0ZL484640F	CP-R-CARBON	RK73H2A 1/10W 464-F TP(TD)	1
				R205	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R206	0ZL481501F	CP-R-CARBON	RK73H2A 1/10W 1.50K-F TP(TD)	1
				R207	0BL4875R0F	CP-R-CARBON	RK73H2E 1/4W 75.0-F TP(TD)	1
				R208	0ZL49332JA	CP-R-CARBON	RK73K2A 1/10W 3.3K-J TP(TD)	1
				R209	0ZL484640F	CP-R-CARBON	RK73H2A 1/10W 464-F TP(TD)	1
				R210	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R211	0ZL481501F	CP-R-CARBON	RK73H2A 1/10W 1.50K-F TP(TD)	1
				R212	0BL4875R0F	CP-R-CARBON	RK73H2E 1/4W 75.0-F TP(TD)	1
				R213	0ZL49332JA	CP-R-CARBON	RK73K2A 1/10W 3.3K-J TP(TD)	1
				R214	0ZL484640F	CP-R-CARBON	RK73H2A 1/10W 464-F TP(TD)	1
				R215	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R216	0ZL49153JA	CP-R-CARBON	RK73K2A 1/10W 15K-J TP(TD)	1
				R217	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R218	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R219	0BL083R3JL	R-FUSING	RF25SJ 1/4W 3.3-J L(L10)	1
				R221	0ZL49101JA	CP-R-CARBON	RK73K2A 1/10W 100-J TP(TD)	1
				R222	0ZL49101JA	CP-R-CARBON	RK73K2A 1/10W 100-J TP(TD)	1
				R223	0ZL49101JA	CP-R-CARBON	RK73K2A 1/10W 100-J TP(TD)	1
				R224	0ZL49471JA	CP-R-CARBON	RK73K2A 1/10W 470-J TP(TD)	1
				R225	0ZL49122JA	CP-R-CARBON	RK73K2A 1/10W 1.2K-J TP(TD)	1
				R226	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
				R227	0ZL49823JA	CP-R-CARBON	RK73K2A 1/10W 82K-J TP(TD)	1
				R228	0ZL49473JA	CP-R-CARBON	RK73K2A 1/10W 47K-J TP(TD)	1
				R229	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
				R351	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R352	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R353	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R354	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R355	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R356	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R357	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R358	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R359	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R360	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R361	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R362	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R363	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				R364	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R365	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R366	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R367	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R368	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R369	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R370	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R371	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R372	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R373	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R374	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R375	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R376	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
				R377	0ZL49104JA	CP-R-CARBON	RK73K2A 1/10W 100K-J TP(TD)	1
				R378	0ZL49104JA	CP-R-CARBON	RK73K2A 1/10W 100K-J TP(TD)	1
				R379	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R380	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R381	0ZL49123JA	CP-R-CARBON	RK73K2A 1/10W 12K-J TP(TD)	1
				R382	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R383	0ZL49221JA	CP-R-CARBON	RK73K2A 1/10W 220-J TP(TD)	1
				R384	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R385	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R386	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R387	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R388	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R389	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R390	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R391	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R392	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R393	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R402	0ZL484702F	CP-R-CARBON	RK73H2A 1/10W 47.0K-F TP(TD)	1
				R404	0ZL482401F	CP-R-CARBON	RK73H2A 1/10W 2.40K-F TP(TD)	1
				R406	0BL081R0JL	R-FUSING	RF25SJ 1/4W 1.0-J L(L10)	1
				R407	0EL09391JL	R-METALOX	RSS 2 L15 390-J	1
				R408	0EL091R0JL	R-METALOX	RSSX 2 L15 1.0-J	1
				R409	0ZL481002F	CP-R-CARBON	RK73H2A 1/10W 10.0K-F TP(TD)	1
				R410	0ZL481102F	CP-R-CARBON	RK73H2A 1/10W 11.0K-F TP(TD)	1
				R411	0FL094R7JL	R-METALOX	RSSX 3 L20 4.7-J	1
				R451	0ZL49823JA	CP-R-CARBON	RK73K2A 1/10W 82K-J TP(TD)	1
				R452	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R453	0ZL49563JA	CP-R-CARBON	RK73K2A 1/10W 56K-J TP(TD)	1
				R454	0ZL49474JA	CP-R-CARBON	RK73K2A 1/10W 470K-J TP(TD)	1
				R455	0ZL49153JA	CP-R-CARBON	RK73K2A 1/10W 15K-J TP(TD)	1
				R456	0ZL483303F	CP-R-CARBON	RK73H2A 1/10W 330.0K-F TP(TD)	1
				R457	0ZL481302F	CP-R-CARBON	RK73H2A 1/10W 13.0K-F TP(TD)	1
				R501	0ZL49104JA	CP-R-CARBON	RK73K2A 1/10W 100K-J TP(TD)	1
				R502	0EL09820JL	R-METALOX	RSS 2 L15 82-J	1
				R503	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
				R505	0ZL49183JA	CP-R-CARBON	RK73K2A 1/10W 18K-J TP(TD)	1
				R506	0ZL49222JA	CP-R-CARBON	RK73K2A 1/10W 2.2K-J TP(TD)	1
				R507	0BL49103JA	CP-R-CARBON	RK73K2E 1/4W 10K-J TP(TD)	1
				R508	0FL095R6JL	R-METALOX	RSSX 3 L20 5.6-J	1
				R511	0DL09150JL	R-METALOX	RSS 1 L12.5 15-J	1
				R512	0CL04104JT	R-CARBON	RD50SS T26 1/2W 100K-J TP	1
				R515	0EL09221JL	R-METALOX	RSS 2 L15 220-J	1
				R516	0EL08220JL	R-FUSING	RF2SJ 2W 22-J L(L20)	1
				R531	0BL49332JA	CP-R-CARBON	RK73K2E 1/4W 3.3K-J TP(TD)	1
				R532	0ZL49123JA	CP-R-CARBON	RK73K2A 1/10W 12K-J TP(TD)	1
				R533	0BL492R2JA	CP-R-CARBON	RK73M2E 1/4W 2.2-J TP(TD)	1
				R535	0FS638R2K2	R-METALOX	RSS 3 FB 8.2-K H2	1
				R536	0BL083R3JL	R-FUSING	RF25SJ 1/4W 3.3-J L(L10)	1
				R601	0ZL49473JA	CP-R-CARBON	RK73K2A 1/10W 47K-J TP(TD)	1
				R602	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R603	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				R604	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R605	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R606	0ZL481802F	CP-R-CARBON	RK73H2A 1/10W 18.0K-F TP(TD)	1
				R607	0ZL481242F	CP-R-CARBON	RK73H2A 1/10W 12.4K-F TP(TD)	1
				R608	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R609	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R610	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R611	0ZL49474JA	CP-R-CARBON	RK73K2A 1/10W 470K-J TP(TD)	1
				R612	0ZL481962F	CP-R-CARBON	RK73H2A 1/10W 19.6K-F TP(TD)	1
				R613	0ZL49154JA	CP-R-CARBON	RK73K2A 1/10W 150K-J TP(TD)	1
				R614	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R615	0ZL49392JA	CP-R-CARBON	RK73K2A 1/10W 3.9K-J TP(TD)	1
				R616	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R617	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R618	0ZL49474JA	CP-R-CARBON	RK73K2A 1/10W 470K-J TP(TD)	1
				R619	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R620	0ZL485601F	CP-R-CARBON	RK73H2A 1/10W 5.60K-F TP(TD)	1
				R621	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R622	0ZL49622JA	CP-R-CARBON	RK73K2A 1/10W 6.2K-J TP(TD)	1
				R623	0ZL49332JA	CP-R-CARBON	RK73K2A 1/10W 3.3K-J TP(TD)	1
				R624	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R625	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
				R626	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
				R627	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
				R628	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R629	0ZL481802F	CP-R-CARBON	RK73H2A 1/10W 18.0K-F TP(TD)	1
				R630	0ZL481132F	CP-R-CARBON	RK73H2A 1/10W 11.3K-F TP(TD)	1
				R631	0ZL49471JA	CP-R-CARBON	RK73K2A 1/10W 470-J TP(TD)	1
				R701	0HM13154JL	R-METAL.OX	SPR 5W 150K-J L(L35)	1
				R702	0CL08680JL	R-FUSING	RF50SJ 1/2W 68-J L(L12.5)	1
				R703	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1
			X	R704	0EL09R27JL	R-METAL.OX	RSSX 2 L15 0.27-J	1
				R711	0DL09820JL	R-METAL.OX	RSS 1 L12.5 82-J	1
			X	R712	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
			X	R713	0ZL49472JA	CP-R-CARBON	RK73K2A 1/10W 4.7K-J TP(TD)	1
			X	R714	0ZL49224JA	CP-R-CARBON	RK73K2A 1/10W 220K-J TP(TD)	1
				R721	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
			X	R722	0ZL49823JA	CP-R-CARBON	RK73K2A 1/10W 82K-J TP(TD)	1
				R723	0ZL49220JA	CP-R-CARBON	RK73K2A 1/10W 22-J TP(TD)	1
				R724	0ZL49220JA	CP-R-CARBON	RK73K2A 1/10W 22-J TP(TD)	1
				R731	0ZL49101JA	CP-R-CARBON	RK73K2A 1/10W 100-J TP(TD)	1
				R732	0DL081R0JL	R-FUSING	RF1SJ 1W 1.0-J L(L15)	1
		S		R901	0CS79224JT	R-METAL.GL	RCP50 T52 220K-J TP	1
		S		R902	0NM161R0KH	R-CEMENT	BGR 15Z RU 1.0-K	1
		S		R903	0CS79224JT	R-METAL.GL	RCP50 T52 220K-J TP	1
		X		R904	0BL49470JA	CP-R-CARBON	RK73K2E 1/4W 47-J TP(TD)	1
				R905	0ZL49220JA	CP-R-CARBON	RK73K2A 1/10W 22-J TP(TD)	1
				R906	0JS65153JV	R-METAL	RSV7FB-15K-J DH	1
				R907	0EL32R15JM	R-METAL.PLATE	BPR 28 2W 0.15-J	1
				R908	0JS65101JV	R-METAL	RSV7FB-100-J DH	1
				R909	0ZL49330JA	CP-R-CARBON	RK73K2A 1/10W 33-J TP(TD)	1
				R910	0ZL49201JA	CP-R-CARBON	RK73K2A 1/10W 200-J TP(TD)	1
				R911	0ZL49683JA	CP-R-CARBON	RK73K2A 1/10W 68K-J TP(TD)	1
				R912	0ELC9333JL	R-METAL.OX	RSS 2 L15 33K-J	1
				R913	0ZL49333JA	CP-R-CARBON	RK73K2A 1/10W 33K-J TP(TD)	1
				R914	0ZL49332JA	CP-R-CARBON	RK73K2A 1/10W 3.3K-J TP(TD)	1
				R915	0ZL49123JA	CP-R-CARBON	RK73K2A 1/10W 12K-J TP(TD)	1
				R916	0ZL49333JA	CP-R-CARBON	RK73K2A 1/10W 33K-J TP(TD)	1
				R917	0ZL49470JA	CP-R-CARBON	RK73K2A 1/10W 47-J TP(TD)	1
				R921	0ZL49682JA	CP-R-CARBON	RK73K2A 1/10W 6.8K-J TP(TD)	1
				R922	0BL49823JA	CP-R-CARBON	RK73K2E 1/4W 82K-J TP(TD)	1
				R923	0BL49683JA	CP-R-CARBON	RK73K2E 1/4W 58K-J TP(TD)	1
				R924	0ZL49122JA	CP-R-CARBON	RK73K2A 1/10W 1.2K-J TP(TD)	1
				R925	0ZL49102JA	CP-R-CARBON	RK73K2A 1/10W 1.0K-J TP(TD)	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				R926	0ZL49202JA	CP-R-CARBON	RK73K2A 1/10W 2.0K-J TP(TD)	1
				R927	0ZL49822JA	CP-R-CARBON	RK73K2A 1/10W 8.2K-J TP(TD)	1
				R928	0ZL49182JA	CP-R-CARBON	RK73K2A 1/10W 1.8K-J TP(TD)	1
				R951	0FM321R5JN	R-WIREWOUND	BWR 3N 1.5-J	1
				R952	0ZL49563JA	CP-R-CARBON	RK73K2A 1/10W 56K-J TP(TD)	1
				R953	0BL49334JA	CP-R-CARBON	RK73K2E 1/4W 330K-J TP(TD)	1
				R954	0ZL49562JA	CP-R-CARBON	RK73K2A 1/10W 5.6K-J TP(TD)	1
				R955	0BL08221JL	R-FUSING	RF25SJ 1/4W 220-J L(L10)	1
				R956	0ZL49683JA	CP-R-CARBON	RK73K2A 1/10W 68K-J TP(TD)	1
				R957	0ZL49224JA	CP-R-CARBON	RK73K2A 1/10W 220K-J TP(TD)	1
				R958	0BL49273JA	CP-R-CARBON	RK73K2E 1/4W 27K-J TP(TD)	1
				R959	0BL49273JA	CP-R-CARBON	RK73K2E 1/4W 27K-J TP(TD)	1
				R960	0ZL49392JA	CP-R-CARBON	RK73K2A 1/10W 3.9K-J TP(TD)	1
				R961	0ZL49222JA	CP-R-CARBON	RK73K2A 1/10W 2.2K-J TP(TD)	1
				R962	0ZL49474JA	CP-R-CARBON	RK73K2A 1/10W 470K-J TP(TD)	1
				R963	0ZL49681JA	CP-R-CARBON	RK73K2A 1/10W 680-J TP(TD)	1
				R964	0ZL49563JA	CP-R-CARBON	RK73K2A 1/10W 56K-J TP(TD)	1
				R965	0ZL49393JA	CP-R-CARBON	RK73K2A 1/10W 39K-J TP(TD)	1
				R971	0ZL49103JA	CP-R-CARBON	RK73K2A 1/10W 10K-J TP(TD)	1
				R972	0ZL49223JA	CP-R-CARBON	RK73K2A 1/10W 22K-J TP(TD)	1
				R973	0ZL49683JA	CP-R-CARBON	RK73K2A 1/10W 68K-J TP(TD)	1
				R975	0ZL49183JA	CP-R-CARBON	RK73K2A 1/10W 18K-J TP(TD)	1
				R976	0ZL49473JA	CP-R-CARBON	RK73K2A 1/10W 47K-J TP(TD)	1
				RY511	09F39101A1	RELAY	JV-12-KT	1
				RY512	09F39101A1	RELAY	JV-12-KT	1
				RY513	09F39101A1	RELAY	JV-12-KT	1
				RY515	09F39101A1	RELAY	JV-12-KT	1
	S			RY901	09F39101A1	RELAY	JV-12-KT	1
				SW351	08F45784T1	SW-TACT	SKHVPA	1
				SW352	08F45784T1	SW-TACT	SKHVPA	1
				SW353	08F45784T1	SW-TACT	SKHVPA	1
				T501	0AF13003A1	TRANS-H.DRIVE	A1400168	1
				T531	0AF13002A1	TRANS	ETS29AC289AC	1
	S	X		T701	05F13749A1	F.B.T	MSU1FUS11 5610220	1
				(T701)	05S90043A1	SCREW	B-TITE-P-TP 3X10 ZN/FE	3
	S			T901	05F13809A1	TRANS	ETS39AF2Z5NC	1
				TP701	00J44862A2	PIN-TP	RT-01T-1.0B	1
				TP921	00J44862A2	PIN-TP	RT-01T-1.0B	1
A				U101	00G8E010AE	CP-IC	TC74HCT86AF-EL	1
A				U201	00G8B004AA	IC	CXA2055P	1
A				U351	00G8D010AA	IC	M37221M4-117SP	1
A				U351	05V20047A1	IC	ASSY MICRON MS-2931	OR
A				(U351)	00G8D006AA	IC	M37221EFSP	1
A				U352	08J26126A1	CP-IC	M51951AML-600C-A	1
A				U353	00G8D004AA	IC	NM24C02EN	1
A				U353	00G8D005AA	IC	24LC02B-1/P	OR
A	M			U354	09F26519T2	CP-IC	M62392FP	1
				U401	09F26068A1	IC	LA7846N	1
				(U401)	09F52087B1	INSULATOR	E-1060	1
A				U451	00J26774A2	CP-IC	M5233FP-600C-B	1
				U531	09F26023A1	IC	LA6500-FA	1
				(U531)	08F52022A1	INSULATOR	M-30(13X18)D-1 DSN-CSSX-G53003	1
				(U531)	00J49987A1	INSULATOR	INSULATOR 25K (B-24)	1
				(U531)	00R49068A2	RADIATOR	OSH-2425-SPL	1
				(U531)	0FF623010D	SCREW	SC-SEMS-P-PAN M3X10(W/SW) ZN/FE	1
				U601	09F26381A1	IC	UPC1883BCT	1
A				U602	08N26343A5	IC	UPC78M09AHF	1
A	S	X		U701	09F26239A1	ASSY PCB-PCS	MSPAC004	1
A	M			U901	00G8C005AD	CP-IC	M62281FP	1
A				U921	01F26854A7	IC	UPC2412AHF	1
A				U922	01F26854A1	IC	UPC2405AHF	1
				U923	08R26113T1	CP-IC	AN1431M	1
A	M			U951	00G8C006AE	CP-IC	M62501FP	1
A				U971	00J26324A3	CP-IC	M5223FP-600C-C	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY
				VR501	00H13473WB	R-SEMX	RH063LCS4R-47KB	1
			X	VR711	00H13103WB	R-SEMX	RH063LC14R-10KB	1
			X	VR721	00H13473WB	R-SEMX	RH063LCS4R-47KB	1
				VR921	00H13102WB	R-SEMX	RH063LC13R-1KB	1
				X351	08R38626A1	CP-OSC	CSACS8.00MT-TC TP(SMD)	1
				ZD101	00N25729B8	D-ZENER	HZS2.7NB2TD	1
				ZD201	00N25709T2	D-ZENER	HZS36-2LTD	1
				ZD202	00N25709T2	D-ZENER	HZS36-2LTD	1
				ZD203	00N25709T2	D-ZENER	HZS36-2LTD	1
				ZD351	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD352	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD353	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD354	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD355	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD356	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD357	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD358	08H25125B4	CP-D-ZENER	MA8056-M (TX)	1
				ZD381	00N25734B3	D-ZENER	HZS11NB3TD	1
				ZD531	00N25498T3	D-ZENER	HZS2CLLTD	1
				ZD601	00N25732B5	D-ZENER	HZS6.8NB2TD	1
			X	ZD711	00N25706T8	D-ZENER	HZS18-2LTD	1
				ZD901	00N25736B5	D-ZENER	HZS22NB2TD	1
				ZD902	00N25739B2	D-ZENER	HZS36NB2TD	1
				(ASSY HV)	08J54319A1	EDGE-SADDLE	EDGE-SADDLE EDS-3	1
				(ASSY HV)	05D07636C1	RADIATOR	RADIATOR PV	1
				(ASSY HV)	05S90043A1	SCREW	TAP-TITE-SCREW B-TITE-P-TP 3X10 ZN/FE	5

A: M S X	SYMB.	CODE	NAME	DESCRIPTION	QTY
***** ASS'Y PCB CRT *****					
	C301	0KH80331JM	C-CERAMIC	DD107-959 SL 331J 50V (TP)	1
	C302	0KH81222KB	C-CERAMIC	DD106-999 B 222K 50V (TP)	1
	C311	0KH80331JM	C-CERAMIC	DD107-959 SL 331J 50V (TP)	1
	C312	0KH81222KB	C-CERAMIC	DD106-999 B 222K 50V (TP)	1
	C321	0KH80331JM	C-CERAMIC	DD107-959 SL 331J 50V (TP)	1
	C322	0KH81222KB	C-CERAMIC	DD106-999 B 222K 50V (TP)	1
	C331	02L81102KB	C-CERAMIC	DE0907-1 B 102K 2KV (SRT)	1
	C332	0RP41100MW	C-EL	1KME 250V 10MF-M MC 10X20	1
	C341	02L81222KB	C-CERAMIC	DE1207-1 B 222K 2KV (SRT)	1
	CN301	00F44547B1	PIN-GT	2364 GT-PIN	1
	CN302	00J40642A5	CONNECTOR	B6B-PH-K-S	1
	CN303	00F40953A4	CONNECTOR	B5B-XH-A	1
	D301	00J25891A1	DIODE	1SS133 T-77	1
	D302	00N25030T1	DIODE	1SS244 T-77	1
	D303	00N25030T1	DIODE	1SS244 T-77	1
	D311	00J25891A1	DIODE	1SS133 T-77	1
	D312	00N25030T1	DIODE	1SS244 T-77	1
	D313	00N25030T1	DIODE	1SS244 T-77	1
	D321	00J25891A1	DIODE	1SS133 T-77	1
	D322	00N25030T1	DIODE	1SS244 T-77	1
	D323	00N25030T1	DIODE	1SS244 T-77	1
	L301	00L13120KT	AXIAL-COIL	LF5.0S 120 T26 K	1
	L302	00L134R7KT	AXIAL-COIL	LF5.0S 4R7 T26 K	1
	L311	00L13120KT	AXIAL-COIL	LF5.0S 120 T26 K	1
	L312	00L134R7KT	AXIAL-COIL	LF5.0S 4R7 T26 K	1
	L313	00L13100KT	AXIAL-COIL	LF5.0S 100 T26 K	1
	L321	00L13100KT	AXIAL-COIL	LF5.0S 100 T26 K	1
	L322	00L134R7KT	AXIAL-COIL	LF5.0S 4R7 T26 K	1
	L323	00L13100KT	AXIAL-COIL	LF5.0S 100 T26 K	1
	L324	00L13120KT	AXIAL-COIL	LF5.0S 120 T26 K	1
	Q301	0CH21740SZ	TR	2SC1740S TP E,Q,R,S	1
	Q302	0CF24001ZL	TR	2SC4001-L	1
	(Q302)	0PF723010Z	SCREW	SC-P-PAN-PC M3X10	1
	(Q302)	38R49039A1	RADIATOR	OSH1025-SPL	1
	(Q302)	08R49039A1	RADIATOR	OSH-1025-SPL	OR
	(Q302)	30N0D023A1	RADIATOR	BPUE10-25	OR
	(Q302)	00N0D023A1	RADIATOR	BPUE10-25	OR
	(Q302)	09F52327A1	INSULATOR	TF RUBBER	1
	Q303	0CH24218ZZ	TR	2SC4218 AA	1
	Q304	0AH21624ZZ	TR	2SA1624 AA	1
	Q311	0CH21740SZ	TR	2SC1740S TP E,Q,R,S	1
	Q312	0CF24001ZL	TR	2SC4001-L	1
	(Q312)	0PF723010Z	SCREW	SC-P-PAN-PC M3X10	1
	(Q312)	38R49039A1	RADIATOR	OSH1025-SPL	1
	(Q312)	08R49039A1	RADIATOR	OSH-1025-SPL	OR
	(Q312)	30N0D023A1	RADIATOR	BPUE10-25	OR
	(Q312)	00N0D023A1	RADIATOR	BPUE10-25	OR
	(Q312)	09F52327A1	INSULATOR	TF RUBBER	1
	Q313	0CH24218ZZ	TR	2SC4218 AA	1
	Q314	0AH21624ZZ	TR	2SA1624 AA	1
	Q321	0CH21740SZ	TR	2SC1740S TP E,Q,R,S	1
	Q322	0CF24001ZL	TR	2SC4001-L	1
	(Q322)	0PF723010Z	SCREW	SC-P-PAN-PC M3X10	1
	(Q322)	38R49039A1	RADIATOR	OSH1025-SPL	1
	(Q322)	08R49039A1	RADIATOR	OSH-1025-SPL	OR
	(Q322)	30N0D023A1	RADIATOR	BPUE10-25	OR
	(Q322)	00N0D023A1	RADIATOR	BPUE10-25	OR
	(Q322)	09F52327A1	INSULATOR	TF RUBBER	1
	Q323	0CH24218ZZ	TR	2SC4218 AA	1
	Q324	0AH21624ZZ	TR	2SA1624 AA	1
	R300	0BK10471JT	R-CARBON	KRDS2T 1/4W 470-J TP	1
	R301	0BK10121JT	R-CARBON	KRDS2T 1/4W 120-J TP	1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	Q'TY
				R302	0BK10220JT	R-CARBON	KRDS2T 1/4W 22-J TP	1
				R303	0CL04224JT	R-CARBON	RD50SS T26 1/2W 220K-J TP	1
				R304	0BK10183JT	R-CARBON	KRDS2T 1/4W 18K-J TP	1
				R305	0HM37562J1	R-CEMENT	BSR5YS 5.6K-J	1
				R306	0BL08101JL	R-FUSING	RF25SJ 1/4W 100-J L(L10)	1
				R307	0CS79271JT	R-METAL GL	RCR50 T52 270-J TP	1
				R308	0BK10102JT	R-CARBON	KRDS2T 1/4W 1.0K-J TP	1
				R310	0BK10471JT	R-CARBON	KRDS2T 1/4W 470-J TP	1
				R311	0BK10121JT	R-CARBON	KRDS2T 1/4W 120-J TP	1
				R312	0BK10220JT	R-CARBON	KRDS2T 1/4W 22-J TP	1
				R313	0CL04224JT	R-CARBON	RD50SS T26 1/2W 220K-J TP	1
				R314	0BK10183JT	R-CARBON	KRDS2T 1/4W 18K-J TP	1
				R315	0HM37562J1	R-CEMENT	BSR5YS 5.6K-J	1
				R316	0BL08101JL	R-FUSING	RF25SJ 1/4W 100-J L(L10)	1
				R317	0CS79271JT	R-METAL GL	RCR50 T52 270-J TP	1
				R320	0BK10471JT	R-CARBON	KRDS2T 1/4W 470-J TP	1
				R321	0BK10121JT	R-CARBON	KRDS2T 1/4W 120-J TP	1
				R322	0BK10220JT	R-CARBON	KRDS2T 1/4W 22-J TP	1
				R323	0CL04224JT	R-CARBON	RD50SS T26 1/2W 220K-J TP	1
				R324	0BK10183JT	R-CARBON	KRDS2T 1/4W 18K-J TP	1
				R325	0HM37562J1	R-CEMENT	BSR5YS 5.6K-J	1
				R326	0BL08101JL	R-FUSING	RF25SJ 1/4W 100-J L(L10)	1
				R327	0CS79271JT	R-METAL GL	RCR50 T52 270-J TP	1
				R331	0CS79105JT	R-METAL GL	RCR50 T52 +1M-J TP	1
				R332	0CG08106JT	R-METAL	RK14B2H 10M-J TP	1
				R341	0CL04473JT	R-CARBON	RD50SS T26 1/2W 47K-J TP	1
				SG301	08R38116A1	SPARK-GAP	RA-102M-V6-Y-2	1
				SG311	08R38116A1	SPARK-GAP	RA-102M-V6-Y-2	1
				SG321	08R38116A1	SPARK-GAP	RA-102M-V6-Y-2	1
				SG333	09F38065A1	SPARK-GAP	RA-231M-V6-Y-2(RADIAL)	1
S				SK301	09F43293A1	CRT-SOCKET	CVT3240-0932	1
				ZD301	00N25735B2	D-ZENER	HZS15N82TD	1
				ZD311	00N25735B2	D-ZENER	HZS15N82TD	1
				ZD321	00N25735B2	D-ZENER	HZS15N82TD	1
				ZZ001	05DC6966A1	PCB-COVER	PCB-COVER MS9-29	1
				ZZ002	08N54089A1	CLAMPER	T18R	1
***** OTHERS *****								
S				00MCA052A1	ASSY-CN-SE	(for -S/SW only)		1
				00MCA016A1	ASSY-CN353	(for -AW only)		1
				00MCA050A1	ASSY-CN352S	(for -AW only)		1
				00MCA051A1	ASSY-CN353S	(for -AW only)		1
				05A20008A1	BASE-2931			1
				08N54105A1	CLAMPER	PLT1M		6
				08N54089A1	CLAMPER	T18R		OR
				05D07812A1	EDGE-COVER			1
				05D20186A1	LABEL	LABEL-CN (for -S/SW only)		1
				05D20154B1	LABEL	LABEL-HV-FUSE		1
				00NCH001A1	NUT	belongs to 00M05007A1		2
				08R66409A1	NUT	belongs to 08R40362A1, A2		OR
S				05B20010A1	PCB-BASE			1
				05C20098A1	PLATE-CN			1
				00R54243A1	PWD-HOLDER	#1429		2
				05S90043A1	SCREW	TAP-TITE-P-TP 3-TYPE 3*10 ZnFe		7
				08N54362A1	WIRE-HOLDER	HL-28-0		1
				08R54031A1	WIRE-SADDLES	LWS-2NA RICHCO		1

A	M	S	X	SYMB.	CODE	NAME	DESCRIPTION	QTY			
								SW	AW	S	A
2. OTHERS											
					.09F51156A1	ANODE RING	ANR-65	1	1	1	1
					.05P20059A1	ASSY COATING EARTH		1	1	1	1
				(C-EARTH)	.00F09500A2	SHIELD-WIRE	120/0.12T	3	3	3	3
				(C-EARTH)	.05D03719A1	SPRING		1	1	1	1
				(C-EARTH)	.05V10564D1	COATING-WIRE		1	1	1	1
				(C-EARTH)	.08N54105A1	CLAMPER	PLT-1M	2	2	2	2
				(C-EARTH)	.08N54089A1	CLAMPER	T18R	OR	OR	OR	OR
S					.3AF16002A1	ASSY DG COIL		1	1	1	1
S					.05P20060A1	ASSY DG COIL		OR	OR	OR	OR
				(DG COIL)	.00N09453A8	WIRE-COPPER	1μEW φ0.6	2	2	2	2
				(DG COIL)	.05V03524A1	DG WIRE		1	1	1	1
				(DG COIL)	.08N54105A1	CLAMPER	PLT-1M	1	1	1	1
				(DG COIL)	.08N54089A1	CLAMPER	T18R	OR	OR	OR	OR
					.05C02749B1	ASSY PALLET		1/2	1/2	/	/
					.05C02911B1	BRACKET	BRACKET-29VGA	2	2	2	2
					.08N50441A1	C.P MAGNET	ETC33X8KA	1	1	1	1
					.00J50821A1	C.P MAGNET	2771831	OR	OR	OR	OR
					.09F54329A1	CLAMPER	T18R-V0	6	6	6	6
S	X				.09F31599A1	CRT	A68LBT696X	1	1	1	1
					.05S90059A1	CRT-SCREW		4	4	4	4
					.05A00737B1	CUSHION	CUSHION-29NF	/	/	2	2
S					.05F18745A1	DY	KDY4UW555R	1	1	1	1
					.05D07063A2	HOLDER	HOLDER-29	4	4	4	4
					.05D20055A1	LABEL	LABEL-HV	4	4	4	4
					.05D06327A1	LABEL	LABEL-S	1	/	1	/
					.05D06983A1	LABEL	LABEL-B	1	/	1	/
					.05D07882B1	LABEL	LABEL-PTB	1	1	1	1
					.05D06444A1	LABEL	DHHS LABEL	1	1	1	1
					.05C02093A1	LABEL	BAR CODE LABEL	1	1	1	1
					.08F50377A1	MAGNET	102 + NITTO No.500	5/2	5/2	5/2	5/2
					.09F50363A1	MAGNET	TIC8016	1	1	1	1
					.09F50364A1	MAGNET	TIC8065B	1	1	1	1
					.05D07401A3	MONITOR-BAG	t=0.05 GREEN	1/2	1/2	/	/
S					.05D20106C1	N.P	N.P-2931-NNO	1	1	1	1
					.05C20055B1	PACKING-CASE		/	/	1	1
					.05D06393A1	PAD	PAD FSG	/	/	1	1
					.05C02935A1	PAD	PAD TOP	/	/	2	2
					.05D07069A1	PALLET-SUPPORTER		1	1	/	/
					.00F55550A1	PLASTI-RIVET	No.615	/	1	/	1
					.08R50047A1	RUBBER MAGNET	B-1030 NITRILE	3	3	3	3
					.0FJ924008D	SCREW	B-TITE-P-BIND 4*8 Zn/Fe	4	4	4	4
					.0FN606014D	SCREW	SCREW-SEMS-P-HEX M6*14 (W/SW) Zn/Fe	5	5	4	4
					.05B01107B1	STAY	STAY-29VGA	2	2	2	2
					.05C02609A1	SUPPORT	SUPPORT-29S	1/2	1/2	/	/
					.05D20107B1	U.M	U.M-2931	1/2	1/2	1	1
					.08N46012A1	WEDGE	WEDGE-31	3	3	3	3
					.00F54549A2	WIRE-HOLDER	11.5B	1	1	1	1
3. ASSEMBLED PARTS											
					.05P20058A1	ASS'Y CHASSIS UNIT	(includes PCBs below)	1	/	1	/
					.05P20058A2	ASS'Y CHASSIS UNIT	(includes PCBs below)	/	1	/	1
S				---	---	ASS'Y PCB MAIN					
S				---	---	ASS'Y PCB CRT					